

## KNX ENO 620/622 (32-channel)

### Gateway between EnOcean and the KNX bus

Data sheet

#### Application

KNX ENO 620 and 622 serve as gateways between EnOcean radio sensors and the KNX bus and offer additional control functionality. A device has 32 sensor channels, each of which can be configured with one of the following functions:

- Switching / Dimming
- Blinds / Shutters
- Temperature sensor
- Window contact
- Light sensor
- Motion detector



Fig.: KNX ENO 620

Touch sensors can be configured as one-key control or as rocker. Up to 4 keys/rockers can be connected to one channel.

In addition, the device contains six control channels that can be connected with the communication objects of a sensor channel or of an external KNX sensor. The following control types can be selected for each channel:

- Light, continuous
- Light, on/off
- Temperature, continuous
- Temperature, on/off
- Common 2-byte-float, on/off
- Common 0...255 (0...100 %), on/off



Fig.: KNX ENO 622

The function of each channel is selected with the ETS software by parameter. Depending on the selected function the enOcean telegrams are mapped to up to 6 communication objects. Linking of sensors can be done with a interface in the device or remot via KNX bus with a separately available software.

#### Technical data

##### Electrical safety

- Protection class (as per EN 60529): IP 20
- Safety extra low voltage SELV 24 VDC
- Compliant with EN 50090-2-2

##### EMC requirements

- Compliant with EN 61000-6-2, EN 61000-6-3 and EN 50090-2-2

##### Ambient conditions

- Climatic stability: EN 50090-2-2
- Ambient operating temp.: - 5 ... + 45 °C
- Storage temp.: - 25 ... + 70 °C
- Rel. humidity (not condens.): 5 % ... 93 %

##### Labeling

- KNX
- CE compliant with EMC requirements (residential and functional buildings)

##### Hardware data

- Housing: plastic, white
- On-wall mounting
- Dimensions KNX ENO 620: 71 x 71 x 27 mm
- Dimensions KNX ENO 622: 85 x 85 x 37 mm
- Weight KNX ENO 620: approx. 70 g
- Weight KNX ENO 622: approx. 90 g
- Fire load: approx. 1000 kJ

##### Power supply

- Powered via bus
- Current consumption: approx. 25 mA

##### Connections

- KNX connection

##### Supported EnOcean devices

- See operating and installation instructions



Weinzierl Engineering GmbH  
 DE-84508 Burgkirchen  
 E-Mail: [info@weinzierl.de](mailto:info@weinzierl.de)  
 Web: [www.weinzierl.de](http://www.weinzierl.de)